

CRS326-24G-2S+RM

We are announcing RouterOS upgraded version of CSS326-24G-2S+RM - CRS326-24G-2S+RM. SwOS/RouterOS powered 24 port Gigabit Ethernet switch with two SFP+ ports, wire speed connectivity with several new switching features!

It has additional CPU unit that allows customers to run full RouterOS operating system on this device. CPU unit offers limited processing power, but is sufficient to run few very needed RouterOS features that common smart switches simply doesn't have.

It has "Dual boot" feature that allows you to choose which operating system you prefer to use, RouterOS or SwOS. If you prefer to have a simplified switch only OS with more switch specific features, use SwOS. If you are used to Winbox and would like the ability to use routing and other Layer 3 features on some ports in your CRS, boot and use RouterOS. You can select the desired operating system from RouterOS, from SwOS or from the RouterBOOT loader settings.

It gives you all the basic functionality for a managed switch, plus more: allows to manage port-to-port forwarding, apply MAC filter, configure VLANs, mirror traffic, apply bandwidth limitation and even adjust some MAC and IP header fields. SFP cage supports both 1.25 Gb SFP and 10 Gb SFP+ modules.

Specifications

Product code	CRS326-24G-2S+RM
CPU	98DX3236A1 800 MHz
RAM	512 MB
Storage type	Flash, 16 MB
Switch chip model	98DX3236A1
10/100/1000 Ethernet ports	24
SFP+ cages	2
Operating system	SwOS /RouterOS (Dual boot)
Supported input voltage	9 - 30 V (jack or passive PoE)
Dimensions	440 x 144 x 44 mm
Operating temperature	-40°C .. +60°C tested
Max power consumption	24 W
Serial port	RJ45

SwOS Features

- Non-blocking Layer 2 switching capacity
- 16K host table
- IEEE 802.1Q VLAN
- Supports up to 4K simultaneous VLANs
- Port isolation
- Port security
- Broadcast storm control
- Port mirroring of ingress/egress traffic
- Rapid Spanning Tree Protocol
- Access Control List
- MikroTik neighbor discovery
- SNMP v1
- Web-based GUI

Included



24 V 1.2 A power adapter



Rack ears

